

Xcel™**Programmable siren****3492L6**

Three-level slide switch can be programmed as independent, semi-progressive, or progressive giving the user more options when configuring the siren. Constant visual identification test of speaker integrity and lighting functions make for the fastest siren diagnostics on the market.

DESIGN FEATURES

- Five rotary switch positions: Standby, Wail, Yelp, Alt Tone, and Radio
- Unique programming features including latching of auxiliary buttons to level outputs allow the officer to keep their eyes on the road for longer periods of time
- Backlighting on buttons can be adjusted to the officer's preference
- Program California T13 compliance with the flip of a switch
- Positive or negative Park-Kill and Horn-Ring transfer triggers allow for easy installation on all vehicle types
- Visual notification of switching and programming functions makes for easy installation and service
- Plug 'n Play fuses and connections make for easy installation and service
- Oversized manual wail and air horn buttons
- Six programmable auxiliary switches with insertable legends
- 11 built-in automotive style fuses
- 12 dip switches for configuring

- Plug 'n Play input/output connectors
- Wail, Yelp, and Alt Tone (Alt Tone can be Hyper-Yelp or Hi-Lo)
- Aux button F can be 8 second timed or on/off
- Aux button E can be configured as hands-free and works with Horn-Ring transfer
- Three-level switch can be split into 3A, and 3B for Park-Kill application
- Horn Ring transfer, Horn Ring always, and Hands Free mode
- Light Alert - low volume audio when buttons are activated
- Siren must be used with ignition
- Banshee siren amp compatible for additional features

OPTIONS

- Siren with or without light functions available
- Mic jack version
- Public address (PA) only available

SPECIFICATIONS

- 6.50" W x 2.75" H x 5.56" D (165 x 69 x 141 mm)
- Operating voltage: 10-16VDC or 24 Volt
- Output capacity: 100W or 200W
- Compliance: SAE J1849, California Title 13 and ECE R10.05 when properly configured
- Three level switch current: Level 1, Level 2, Level 3A, Level 3B, capable of 15 amp each for a combined total of 50 amp
- Auxiliary switches: Aux A - Aux F capable of 10 amp each
- 5-year warranty

